




TBLU

A 5W, 25/70V transformer with 5 taps at -3dB levels each, and 7" color-coded leads.



TCH70

A 10W, 70V low-loss, extended low frequency transformer with 5 taps at -3dB levels each, and 7" color-coded leads.



APPLICATION

Intended Use:
Program Material:
Installation:

Indoor environment
Signal tones, voice and music
• Desired tap/common primary leads connected to the output of a constant voltage amplifier
• Secondary/common attached to a nominal 8 Ohm loudspeaker

Indoor environment
Signal tones, voice and music
• Desired tap/common primary leads connected to the output of a constant voltage amplifier
• Secondary/common attached to a nominal 8 Ohm loudspeaker

AUDIO PERFORMANCE

Primary Voltage: 25V, 70V
Maximum Power Rating: 5W
Primary Taps (-3 dB Steps): 0.31W, 0.63W, 1.25W, 2.5W, 5W
Secondary Load: 8 Ohms, Nominal
Frequency Response: 100Hz - 15kHz
Insertion Loss: 1.0 dB

70V
10W
0.63W, 1.25W, 2.5W, 5W, 10W
8 Ohms, Nominal
50Hz - 20kHz
0.75 dB

MECHANICAL SPECIFICATIONS

Dimensions: 1 1/16" (H) x 1 1/16" (W) x 1 1/2" (D)
Primary Connection: 7", Color-coded, Pre-tinned Leads
Secondary Connection: 6", Color-coded, Pre-tinned Leads

2" (H) x 1 1/16" (W) x 1 1/2" (D)
12", Color-coded, Pre-tinned Leads
6", Color-coded, Pre-tinned Leads

RECOMMENDED QUAM COMPONENTS

Loudspeaker: Quam 8 Ohm loudspeakers

Quam 8 Ohm loudspeakers

